

## 36W LED Retrofit Lamp

Order Code: LP38326



#### Description

Venture Lighting's LED Retrofit lamps are the ideal upgrade solution to traditional HID lamp technologies. Venture's LED Retrofit lamps are a simple energy saving solution for providing significant maintenance savings. The integrated driver design is an ideal upgrade from traditional technologies.

#### Feature & Benefits

- Energy Saving Replacement for MH or HPS
- Up to 5 times longer life and 80% energy savings compared to HID
- 5 year warranty
- Universal burn position
- Easy installation
- Reduced maintenance costs

#### **Applications**

- Post top
- Wallpack
- Area lighting
- Flood lighting
- Garage lighting
- General illumination

#### Notes

- The use of an external surge protection device is recommended
- Operating temp. range between -40°F and 113°F (-40°C and 45°C)
- Suitable for use in open and enclosed luminaires
- Suitable for use in dry and damp environments
- Do not use where exposed to water or outdoors without an appropriate enclosed
- Lamps have clear polycarbonate cover lenses

For warranty information refer to: www.venturelighting.com/resources/warranties

Product Performance	
Input Power (W)	36
Initial Lumens	5075
Lumens/Watt	140
Correlated Color Temperature (CCT)	4000K
Color Rendering Index (CRI)	80
Life Hours	50000
Min. Lamp Compartment (H x L x W)	14.96" x 7.87" x 7.87" (380mm x 200mm x 200mm)
Dimming	No
Operating Temperature Range	-40°F to 113°F (-40°C to 45°C)

Physical Characteristics	
Base Type	Medium (E26)
Overall Length A	7.56" (192mm)
Diameter B	3.35" (85mm)
Weight	1.23 lbs (0.56 kg)

Electrical Characteristics	
Input Voltage Range	100-277V; 50/60Hz
Power Factor	<u>≥</u> 90%
THD	<u>≤</u> 20%

Regu	laton	/ Ou	alifi	catio	าทร
NUSU	ιαισι	/ Qu	um	can	כווע

cULus Listed (UL 1993/CSA C22.2 No. 1993)

cULus Classified (UL 1598C/CSA C22.2 No. 250.1)

### Accessories


SP12714 120-277V Surge Protector


Revision: 02, 07-Sept 2022





# Venture 36W LED Retrofit Lamp





Easy to install - bypass ballast and provide voltage directly to lamp

### (800) 451-2606

6675 Parkland Blvd., Suite 100 Solon, Ohio 44139 USA Email: Venture\_Lighting@VentureLighting.com



